QR Decomposition with Gram-Schmidt

The QR decomposition (also called the QR factorization) of a matrix is a decomposition of the matrix into an orthogonal matrix and a triangular matrix. A QR decomposition of a real square matrix A is a decomposition of A as

$$A = QR$$

where Q is an orthogonal matrix (i.e. $Q^TQ = I$) and R is an upper triangular matrix. If A is nonsingular, then this factorization is unique.

There are several methods for actually computing the QR decomposition. One of such method is the Gram-Schmidt process.

1 Gram-Schmidt process

Consider the GramSchmidt procedure, with the vectors to be considered in the process as columns of the matrix A. That is,

$$A = \left[\mathbf{a}_1 \mid \mathbf{a}_2 \mid \cdots \mid \mathbf{a}_n \right].$$

Then,

Note that $||\cdot||$ is the L_2 norm.

1.1 QR Factorization

Note that once we find $\mathbf{e}_1, \dots, \mathbf{e}_n$, it is not hard to write the QR factorization.

2 Example

Consider the matrix

$$A = \left[\begin{array}{ccc} 1 & 1 & 0 \\ 1 & 0 & 1 \\ 0 & 1 & 1 \end{array} \right],$$

with the vectors $\mathbf{a}_1 = (1, 1, 0)^T$, $\mathbf{a}_2 = (1, 0, 1)^T$, $\mathbf{a}_3 = (0, 1, 1)^T$.

Note that all the vectors considered above and below are column vectors. From now on, I will drop T notation for simplicity, but we have to remember that all the vectors are column vectors.

Performing the Gram-Schmidt procedure, we obtain:

$$\begin{array}{rcl} \mathbf{u}_1 & = & \mathbf{a}_1 = (1,1,0), \\ \mathbf{e}_1 & = & \frac{\mathbf{u}_1}{||\mathbf{u}_1||} = \frac{1}{\sqrt{2}}(1,1,0) = \left(\frac{1}{\sqrt{2}},\frac{1}{\sqrt{2}},0\right), \\ \\ \mathbf{u}_2 & = & \mathbf{a}_2 - (\mathbf{a}_2 \cdot \mathbf{e}_1)\mathbf{e}_1 = (1,0,1) - \frac{1}{\sqrt{2}}\left(\frac{1}{\sqrt{2}},\frac{1}{\sqrt{2}},0\right) = \left(\frac{1}{2},-\frac{1}{2},1\right), \\ \\ \mathbf{e}_2 & = & \frac{\mathbf{u}_2}{||\mathbf{u}_2||} = \frac{1}{\sqrt{3/2}}\left(\frac{1}{2},-\frac{1}{2},1\right) = \left(\frac{1}{\sqrt{6}},-\frac{1}{\sqrt{6}},\frac{2}{\sqrt{6}}\right), \\ \\ \mathbf{u}_3 & = & \mathbf{a}_3 - (\mathbf{a}_3 \cdot \mathbf{e}_1)\mathbf{e}_1 - (\mathbf{a}_3 \cdot \mathbf{e}_2)\mathbf{e}_2 \\ & = & (0,1,1) - \frac{1}{\sqrt{2}}\left(\frac{1}{\sqrt{2}},\frac{1}{\sqrt{2}},0\right) - \frac{1}{\sqrt{6}}\left(\frac{1}{\sqrt{6}},-\frac{1}{\sqrt{6}},\frac{2}{\sqrt{6}}\right) = \left(-\frac{1}{\sqrt{3}},\frac{1}{\sqrt{3}},\frac{1}{\sqrt{3}}\right), \\ \\ \mathbf{e}_3 & = & \frac{\mathbf{u}_3}{||\mathbf{u}_3||} = \left(-\frac{1}{\sqrt{3}},\frac{1}{\sqrt{3}},\frac{1}{\sqrt{3}}\right). \end{array}$$

Thus,

$$Q = \begin{bmatrix} \mathbf{e}_1 & \mathbf{e}_2 & \cdots & \mathbf{e}_n \end{bmatrix} = \begin{bmatrix} \frac{1}{\sqrt{2}} & \frac{1}{\sqrt{6}} & -\frac{1}{\sqrt{3}} \\ \frac{1}{\sqrt{2}} & -\frac{1}{\sqrt{6}} & \frac{1}{\sqrt{3}} \\ 0 & \frac{2}{\sqrt{6}} & \frac{1}{\sqrt{3}} \end{bmatrix},$$

$$R = \begin{bmatrix} \mathbf{a}_1 \cdot \mathbf{e}_1 & \mathbf{a}_2 \cdot \mathbf{e}_1 & \mathbf{a}_3 \cdot \mathbf{e}_1 \\ 0 & \mathbf{a}_2 \cdot \mathbf{e}_2 & \mathbf{a}_3 \cdot \mathbf{e}_2 \\ 0 & 0 & \mathbf{a}_3 \cdot \mathbf{e}_3 \end{bmatrix} = \begin{bmatrix} \frac{2}{\sqrt{2}} & \frac{1}{\sqrt{2}} & \frac{1}{\sqrt{2}} \\ 0 & \frac{3}{\sqrt{6}} & \frac{1}{\sqrt{6}} \\ 0 & 0 & \frac{2}{\sqrt{3}} \end{bmatrix}.$$